

# ME 3801

## WALL-MOUNT EMERGENCY MICROPHONE



#### Description

ME 3801 is a wall-mount emergency microphone exclusively dedicated to DXT 3000 Voice Alarm system, and can be used for live announcements during emergency situations. It features complete self-diagnostic functionalities and system status reporting in compliance with EN 54-16:2008 standard. Up to four microphones can be daisy-chained on the line, the first of those has emergency functions and it is powered directly by the master unit, while the others need local 24 V DC adapters.

#### **Features**

- > Live emergency announcements
- › General call functionality
- > Complete self-diagnostic
- > Powered by master unit
- > Handheld microphone with PTT button
- > Robust metal case

**Part Number** 

14322030 ME 3801

White

EAN 8024530015732





# ME 3801

### WALL-MOUNT EMERGENCY MICROPHONE

#### Line Art 2D







#### **TECHNICAL SPECIFICATIONS**

Microphone specifications

Туре

Dynamic Directivity Omnidirectional

Sensitivity Frequency Response (-3dB) -70 dB

Output impedance (ohm)

300 Hz ÷ 6000 kHz 500.00 ohm

Console Type

Emergency

Working with General call

DXT 3000

Preamplified

Operating voltage

Yes

Yes

LED indicators

Yes

Power requirement

**Console specifications** 

Connectors

24.00V ~ Hz

Connections

RJ45

Cable

J-Type fire-rated

Daisy-chain

Yes

Max number in daisy-chain

4

Interlock

Yes

**Functionalities Accessories**  Priority

Yes

Cable included

CPR number

Yes 5

Cable length (m) Safety agency

CE compliant

Standard compliance

EN54-16 certified

0068-CPR-007/2015

**Physical specifications** 

Cabinet/Case Material

Metal

Size

Color White Height 210 mm / 8.27 inches

Width 115 mm / 4.53 inches Depth 36 mm / 1.42 inches 1.14 kg / 2.51 lbs Weight

**Technical Specifications** Page 2 of 3



# ME 3801

## WALL-MOUNT EMERGENCY MICROPHONE

#### **ACCESSORIES**

Cables Electronics CJ 428CAT 12399047 8024530016449 AC AD2405 14380022 8024530007027

Technical Specifications Page 3 of 3